



ADAPT-ANT5X-SMAFR
ADAPT-MIM5X-SMAFR



ADAPT-ANT5X-SMAFR



ADAPT-MIM5X-SMAFR

ANTENAS/ANTENNAS

ACESSÓRIOS

ACCESSORIES /ACCESORIOS

- Conecte Antenas com interface N5-5X Twist-on a rádios conectorizados
Connect Antennas with N5-5X Twist-on Interface to connectorized radios/
Conecte antenas con interfaz N5-5X Twist-on a radios conectorizados
- Conecte Rádios com interface N5-5X Twist-on a antenas conectorizadas
Connect Radios with N5-5X Twist-on Interface to connectorized antennas/
Conecte Radios con Interfaz N5-5X Twist-on a antenas conectorizadas

ESPECIFICAÇÕES

SPECIFICATIONS/ESPECIFICACIÓN

	ADAPT-ANT5X-SMAFR	ADAPT-MIM5X-SMAFR
Frequência de operação <i>Frequency range/Rango de operación</i>		4.9-6.425 GHz
VSWR		<1.6:1 (max)
Isolação entre portas <i>Port-to-Port Isolation/Aislamiento entre puertas</i>		<15dB
Perda de Transmissão <i>Transmission Loss/Pérdida de Transmisión</i>	0.5 dB	0.5 dB
Rosca <i>Thread/Rosca</i>	Fêmea (Monta na Antena) Female (Mounts on the antenna) Hembra (se Monta en la Antena)	Macho (Monta na Rádio) Male (Mounts on the Radio) Macho (se Monta en lo Radio)
Conector <i>Connector/ Conector</i>		SMA Fêmea Reverso SMA Female reverse SMA Hembra reverso
Embalagem <i>Package/ Embalaje</i>	100mmx100mmx100mm - 0,3 kg	